

LETTER TO THE EDITOR

Bi-Hamiltonian structure of an integrable Hénon–Heiles system

Regis Caboz†, Vincent Ravoson† and Ljubomir Gavrilov‡

† Laboratoire de Physique Appliquée, Université de Pau et des Pays de l'Adour, Avenue de l'Université, 64000 Pau, France

‡ Institute of Mathematics, Bulgarian Academy of Sciences, 1090 Sofia, Bulgaria

Received 21 February 1991, in final form 21 March 1991

Abstract. By making use of the system of coordinates in which the separation of the variables in the Hamilton–Jacobi equation takes place, we find a bi-Hamiltonian structure of a two degrees of freedom Hamiltonian system corresponding to the integrable Hénon–Heiles Hamiltonian $H = \frac{1}{2}(p_1^2 + p_2^2 + Aq_1^2 + Bq_2^2) - q_1^2q_2 - 2q_2^3$.

Let there be given on \mathbb{R}^n a Hamiltonian vector field v for the Poisson structure (Poisson bracket) V . It means that the flow of v preserves V , or equivalently, there exists a smooth Hamiltonian function H_V such that $v = V[\cdot, H_V]$ (see [2]). Suppose now that v preserves a second Poisson structure W . If V and W are everywhere non-degenerate and compatible (i.e. all of their linear combinations $\lambda V + \mu W$ are also Poisson structures) then the following theorem holds.

Theorem (Dorfman and Gel'fand [2, 4]). There exists a sequence of smooth functions $\{f_k\}$, such that:

- (a) f_1 is a Hamiltonian of the vector field v with respect to V ;
- (b) the vector field of the V Hamiltonian f_k coincides with the vector field of the W Hamiltonian f_{k+1} ;
- (c) the functions $\{f_k\}$ are in involution with respect to both Poisson brackets.

The importance of the above theorem lies in the fact that in certain cases the arising series $\{f_k\}$ of functions in involution provides for the complete integrability of the vector field v .

To our knowledge, however, the known examples of finite-dimensional vector fields satisfying the conditions of the above theorem fall within two groups:

- (i) systems with Casimir functions, i.e. the brackets V and W are degenerate (such as the Toda lattice [2]);
- (ii) systems which can be presented as a direct product of two other Hamiltonian systems (the existence of a second Poisson structure is trivial).

Definition. The Hamiltonian system

$$\frac{d}{dt}f = V[f, H_v] \tag{1}$$

possesses a bi-Hamiltonian structure provided that there exist a function $\rho \neq 0$ and a Poisson structure W such that:

- (i) the flow of the vector field $\rho V[\cdot, H_V]$ preserves W ;
- (ii) the corresponding first integrals H_V and H_W are functionally independent.

If (1) is a two degrees of freedom system having a bi-Hamiltonian structure then it is completely integrable. The second integral H_W is easily reconstructed from the Poisson structures V, W and the functions ρ, H_V . If $N > 2$ then it is an open question whether the Dorfman-Gel'fand theorem can be generalized for systems having a bi-Hamiltonian structure with $\rho \neq \text{constant}$.

In the present letter we shall find a bi-Hamiltonian structure (with $\rho \neq \text{constant}$) of a two degree of freedom Hamiltonian system (1) which does not fall within the two groups of examples described above.

Let H be the following integrable Hénon-Heiles Hamiltonian [3]:

$$H = \frac{1}{2}(p_1^2 + p_2^2 + Aq_1^2 + Bq_2^2) - q_1^2 q_2 - 2q_2^3 \tag{2}$$

and V be the standard Poisson structure on $\mathbb{R}^4\{p_1, p_2, q_1, q_2\}$

$$V = \frac{\partial}{\partial q_1} \wedge \frac{\partial}{\partial p_1} + \frac{\partial}{\partial q_2} \wedge \frac{\partial}{\partial p_2}.$$

The second integral of the system (1) reads

$$F = q_1^4 + 4q_1^2 q_2^2 + 4p_1(p_1 q_2 - p_2 q_1) - 4Aq_1^2 q_2 + (4A - B)(p_1^2 + Aq_1^2).$$

We shall use the following (u, v) variables which are known to be separable for the corresponding Hamilton-Jacobi equation [1, 5]

$$q_1^2 = -4uv \quad q_2 = u + v + (B - 4A)/4. \tag{3}$$

The canonical variables (p_u, p_v, u, v) on $T^*\mathbb{R}^2$ are given by

$$p_1 = \frac{(-uv)^{1/2}(p_u - p_v)}{u - v} \quad p_2 = \frac{up_u - vp_v}{u - v}. \tag{4}$$

In these new variables the integrals of motion take the form

$$H = \{4up_u^2 - 4vp_v^2 - 16(u^4 - v^4) + 8(6A - B)(u^3 - v^3) + (B - 4A)(12A - B)(u^2 - v^2) + A(4A - B)^2(u - v)\}/8(u - v)$$

$$F = uv\{4p_u^2 - 4p_v^2 - 16(u^3 - v^3) + 8(6A - B)(u^2 - v^2) + (B - 4A)(12A - B)(u - v)\}/(u - v)$$

and

$$V = \frac{\partial}{\partial u} \wedge \frac{\partial}{\partial p_u} + \frac{\partial}{\partial v} \wedge \frac{\partial}{\partial p_v}.$$

A direct computation gives

$$\begin{aligned} \frac{\partial F}{\partial u} &= 8v \frac{\partial H}{\partial u} & \frac{\partial F}{\partial v} &= 8u \frac{\partial H}{\partial v} \\ \frac{\partial F}{\partial p_u} &= 8v \frac{\partial H}{\partial p_u} & \frac{\partial F}{\partial p_v} &= 8u \frac{\partial H}{\partial p_v}. \end{aligned} \tag{5}$$

The identities (5) suggest to define a new Poisson structure

$$W = u \frac{\partial}{\partial u} \wedge \frac{\partial}{\partial p_u} + v \frac{\partial}{\partial v} \wedge \frac{\partial}{\partial p_v}.$$

Proposition. (V, W) provides a bi-Hamiltonian structure of the Hamiltonian system (1) where H is the integrable Hénon-Heiles Hamiltonian (2).

Proof. One trivially verifies that W satisfies the Jacobi identity and hence W is a Poisson structure. Using (5) we obtain $V[\cdot, H] = \rho W[\cdot, F]$, where $\rho = 8uv = -2q_1^2$. \square

In the initial coordinates (p_1, p_2, q_1, q_2) the second Poisson structure W takes the form

$$W = \frac{1}{2}q_1 \frac{\partial}{\partial q_1} \wedge \frac{\partial}{\partial p_2} + \frac{1}{2}q_1 \frac{\partial}{\partial q_2} \wedge \frac{\partial}{\partial p_1} + \left(q_2 + \frac{4A-B}{4} \right) \frac{\partial}{\partial q_2} \wedge \frac{\partial}{\partial p_2} - \frac{1}{2}p_1 \frac{\partial}{\partial p_1} \wedge \frac{\partial}{\partial p_2}. \quad (6)$$

Let us define now a third Poisson structure

$$U = \frac{1}{u} \frac{\partial}{\partial u} \wedge \frac{\partial}{\partial p_u} + \frac{1}{v} \frac{\partial}{\partial v} \wedge \frac{\partial}{\partial p_v}.$$

The same arguments as above show that (U, V) provides a bi-Hamiltonian structure of the Hamiltonian vector field $V[\cdot, F]$, as $V[\cdot, F] = \rho U[\cdot, H]$, where $\rho = 8uv = -2q_1^2$. In the initial coordinates (p_1, p_2, q_1, q_2) the Poisson structure U reads

$$U = \frac{B-4A+4q_2}{q_1^2} \frac{\partial}{\partial q_1} \wedge \frac{\partial}{\partial p_1} + \frac{2}{q_1} \frac{\partial}{\partial q_1} \wedge \frac{\partial}{\partial p_2} + \frac{2}{q_1} \frac{\partial}{\partial q_2} \wedge \frac{\partial}{\partial p_1} - \frac{2p_1}{q_1^2} \frac{\partial}{\partial p_1} \wedge \frac{\partial}{\partial p_2}.$$

Finally we note that the three Poisson structures U, V, W , turn out to be compatible each to the other.

Acknowledgments are due to J P Francoise for valuable discussions.

References

- [1] Ankiewicz A and Pask C 1983 The complete Whittaker theorem for two-dimensional integrable systems and its applications *J. Phys. A: Math. Gen.* **16** 4203-8
- [2] Arnold V I and Givental A B 1990 Symplectic Geometry *Dynamical Systems IV, Encyclopaedia of Mathematical Sciences* ed V I Arnold and S P Novikov (Berlin: Springer)
- [3] Bountis T, Segur H and Vivaldi F 1983 Integrable Hamiltonian systems and Painlevé property *Phys. Rev. A* **25** 1257-64
- [4] Dorfman I Ya and Gel'fand I M 1982 Hamiltonian operators and the classical Yang-Baxter equation *Funct. Anal. Appl.* **16** 241-8
- [5] Wojciechowski S 1984 Separability of an integrable case of the Hénon-Heiles system *Phys. Lett.* **100A** 277-8